

CP-R27

DESFire EV1 / MIFARE Classic EV1 Desktop Programmer

Datasheet



Introduction

The CP-R27 is a new contactless smart card and desktop programmer to read/write 13.56 MHz technology, including MIFARE Classic EV1 and MIFARE DESFire EV1. It is compliant with ISO14443A/B.

Using the CP-R27 from Rosslare, installers, and customers can easily program on-site their credentials and prepare the configuration card for configuring their readers.

The CP-R27 is designed as a Plug & Play smart card programmer with a USB port, and is suitable for various smart card applications, such as smart card issuing and programming, personal identification.

Main Features

- Supports ISO/IEC18092 NFC peer-to-peer mode
- Support high-level command of MIFARE DESFire EV1 (DES/3DES, 3k3DES, AES) on hardware
- Supports high speed of ISO14443 up to 424 kbps
- Excellent and compact design

Specifications

Electrical Characteristics	
Power Supply (from USB)	5 VDC (±5%)
Current Consumption	<120 mA
Data Specifications	
Communication Rate	106 -424 kbps High speed transaction
Baud Rate	9600 to 115200 bit/s (default 115200)
Indication	Controllable two-color LED, one buzzer: <ul style="list-style-type: none"> Red LED for Power state Green LED for Normal Reading state
Interface	USB (USB supplies power)
Communication Cable	1.5 meter long USB communication cable
Frequency	13.56 MHz; APDU command
Environmental Characteristics	
Operating Temp. Range	0°C to 60°C (32°F to 140°F)
Storage Temp Range	-10°C to 65°C (22°F to 149°F)
Operating Humidity Range	5 to 95% RH (non-condensing)
Standards	
Contactless	ISO14443A 4(part 1-4), MIFARE Classic EV1, MIFARE DESFire EV1, ISO14443B
Physical Characteristics	
Weight	79 g (2.8 oz)
Dimensions (L x W x H)	116 x 67 x 14 mm (4.6 x 2.6 x 0.6 in.)



• EN ISO 13485



MIFARE® DESFire®, MIFARE Plus®, MIFARE Classic® and MIFARE Ultralight® are registered trademark of NXP B. V. | All product names, logos, and brands are property of their respective owners.

DISCLAIMER: The data contained within Rosslare's materials or documentation is intended to provide only general information about products available for purchase from Rosslare Enterprises Ltd. and its associated companies ("Rosslare"). Reasonable efforts have been made to ensure the accuracy of this information. However, it might contain typographic errors, inaccuracies, or omissions that may relate to product descriptions, visual pictures, specifications, and other details. All technical specifications weights, measures and colors shown, are best approximations. Rosslare can not be held responsible and assumes no legal liability for the accuracy or completeness of the information provided. Rosslare reserves the right to change, delete, or otherwise modify the information, which is represented, at any time, without any prior notice.

© 2021 Rosslare Enterprises Ltd. All rights reserved.

For more information regarding support, visit <https://support.rosslaresecurity.com>.