AxTraxPro[™] V28.0.1.x Access Control Management Software

Datasheet

■ AxTraxPro

Introduction

Rosslare introduces the new AxTraxPro[™] client-server software management platform that enables setting automated physical access control policy across facilities, perfect for today's most demanding users and organizations. The system can manage thousands of Rosslare networked access controllers and users, providing enhanced security with excellent system scalability and performance.

AxTraxPro offers a friendly web-based and soon to be launched mobile application interfaces that allow system operators to locally or remotely manage their on-premise AxTraxPro servers.

Integrated with video management systems and combining Rosslare state-of-the-art access control components – including controllers, readers, credentials, and other peripherals – the complete ecosystem is optimal for almost any need.

Main Features

AxTraxPro enables organizations to meet their dynamic needs with agility and performance like never before.

Leveraging a set of features designed to maximize utility and security, AxTraxPro includes new tools to save time and resources when building the physical access control environment.

- Web client For on-going management of the on-premise AxTraxPro server. Operators can access the system from their web browsers for daily tasks, such as doors and users management, lockdown operation, viewing events, alerts, and reports.
- Enhanced security Communication is secured from the credential all the way to server using advanced encryption algorithms.
- Lockdown For lockdown groups immunity configuration and management.¹
- Video integration Integrated with major NVR vendors, including Hikvision and Dahua, for event-based video pop-up and snapshot reports.
- Integrated biometrics Integrated with Rosslare fingerprint and face Biometric devices to enable improved facility security.
- Access control policies Enhanced access control policies such as access groups, access level¹, interlock groups, Antipassback and more.
- Identity management Managing user information, photo, access credentials and related access policies, using new secure login process with dual-factor authentication dialog.
- Up to 16 credentials per user Supports Face-ID, Fingerprint, PIN-Codes, RFID cards, UHF Tags, NFC-ID, BLE-ID, and LPR for vehicles.
- Alarm management and reporting Alarm management workflow across devices and smart



¹Only with AC-825IP controller.

links automations, email notifications and reports module.

- Ironclad software security Client-server security mechanism including AES 256-bit encryption communication for a privacy compliant system.¹
- **Time and attendance** Built-in capability of generating attendance reports with preset formats, automatic and customized reports.
- **Car parking management** Integrated with 3rd party and Rosslare products for automated gate opening and touchless experience. Including UHF readers, license plate cameras, and mobile credentials, along with fundamental features related to parking occupancy management and control.

Specifications

COMPUTER SPECIFICATIONS	
Operating system	Windows 11 64-bit, Windows 10 64-bit, Windows Server 2016 and above
CPU	Minimum: Intel Core i5, 2.4 GHz or faster processor Recommended: Intel Core i7, 4 cores or more, 2.4 GHz or faster processor
Network	100MB Ethernet connection
Memory	Minimum: 8GB RAM Recommended: 16GB
Hard Disk	Minimum 8GB free space, SSD strongly recommend
WEB CLIENT	
Supported browsers	Mozilla Firefox, Apple Safari, Google Chrome, Microsoft Edge, Opera
DATA BASE FEATURES (DB)	
DB version	Microsoft SQL 2019
DB Backup	Schedule a backup
	Export, import, and erase options
DB retention	Programmable period
MAIN FEATURES	
User capacity	AC-215: 5,000 AC-215B/IPB, AC-225B/IPB, AC-425B/IPB: 30,000 AC-825IP: 100,000
	Up to 16 credentials per user and user credential double authentication by reader and time zone
Event capacity	AC-215: 5,000 AC-215IP, AC-215-B/AC-215IP-B, AC-225/225IP, AC-225-B/225IP-B, AC-425/425IP, AC-425-B/425IP-B: 20,000 AC-825IP: 500,000
Networks	1024 controllers Up to 10,000 readers

Specifications

MAIN FEATURES	
Supported Access Controller Models	AC-215/215IP, AC-215-B/215IP-B, AC-215/215IP-DIN
	AC-225/225IP, AC-225-B/225IP-B, AC-225-DIN with MD-D02, MD-I084 expansions
	AC-425/425IP, AC-425-B/425IP-B, AC-425-DIN with MD-D04, MD-I084 expansions
	AC-825IP with R/S/D/P-805 expansions
Security Communication ¹	OSDP V2 including secure channel
	AES 256-bit symmetric data encryption
Controller Network Communication Interface	Wiegand
	Proprietary RS-485 with AC-215x, AC-225x, AC-425x
	Serial (RS-232/485), TCP-IP
Time zones	Up to 256 time zones that can be assigned to Access/Reports/Update
Holidays	Up to 64 holiday dates, synchronizes with MS Outlook
Supports multiple reader modes	PIN only, PIN and card, PIN or card, card only, Desktop
Alarm to alert	Advanced event color coding of Tamper/Ajar/Forced/Antipassback/Input Alarm events with confirmation status/Email Notifications
User dual authentication	The reader grants access only for two credentials per user per access.

¹Only with AC-825IP controller.

MIFARE and MIFARE Classic are trademarks of NXP B.V. | MIFARE and MIFARE Plus are registered trademarks of NXP B.V. | MIFARE and MIFARE Ultralight are registered trademarks of NXP B.V. | All product names, logos, and brands are property of their respective owners.

DISCLAIMER: The data contained within Rosslare's materials or documentation is intended to provide only general information about products available for purchase from Rosslare Enterprises Ltd. and its associated companies ("Rosslare"). Reasonable efforts have been made to ensure the accuracy of this information. However, it might contain typographic errors, inaccuracies, or omissions that may relate to product descriptions, visual pictures, specifications, and other details. All technical specifications weights, measures and colors shown, are best approximations. Rosslare can not be held responsible and assumes no legal liability for the accuracy or completeness of the information provided. Rosslare reserves the right to change, delete, or otherwise modify the information, which is represented, at any time, without any prior notice.

© 2022 Rosslare Enterprises Ltd. All rights reserved.

For more information regarding support, visit https://support.rosslaresecurity.com.